

## **DIFFERENTIAL PROBE SELECTION GUIDE**

<b>MODEL</b>	<b>PINTEK DP-25</b>	<b>PINTEK DP-30</b>	<b>PINTEK DP-40</b>	<b>PINTEK DP-50</b>	<b>PINTEK DP-14K</b>	<b>PINTEK DP-20K</b>	<b>PINTEK DP-150</b>	<b>PINTEK DP-200</b>	<b>TEKXX P5200</b>	<b>TEKXX P5205</b>	<b>TEKXX P5210</b>
<b>FEATURE</b>	Economic (1300V)	Super High Sensitivity	650V Mid -Low Voltage	Economic (6500V)	14KV High Voltage	20KV Super High Voltage	Super High Range	Super High Frequency	Economic 1300V	High Frequency 100MHz	High Voltage 5600V
<b>Band Width</b>	25MHz	30MHz	40MHz	50MHz	75MHz	20MHz	150MHz	200MHz	25MHz	100MHz	50MHz
<b>Max Input Range (AC-p-p)</b>	20mV ~1300V	1mV ~65V	10mV ~650V	100mV ~6500V	200mV ~14KV	300mV ~20KV	10mV ~10KV	20mV ~2000V	50mV ~1300V	50mV ~1300V	100mV ~5600V
<b>Attenuator Selection</b>	3/x20, ,x50,x200	3/x1,x2 x10	3/x10 x20,x100	4/x100, x200,x500, x1000	4/x200, x400,x1000 x2000	4/x300, x600,1500 x3000	5/x10,x30, x100,x300, x1000	4/x20,x50 x100,x200	2/x50, x500	2/x50, x500	2/x100, x1000
<b>Input Impedance (Differential R/C)</b>	4MΩ 1.7PF	2MΩ 1.7PF	4MΩ 1.7PF	54MΩ 1.25PF	100MΩ 1.25PF	100MΩ 1.25PF	100MΩ 1.25PF	18MΩ 1.7PF	8MΩ 3.5PF	8MΩ 3.5PF	16MΩ 3.5PF
<b>Input R (Each Input R/C)</b>	2MΩ 3.4PF	1MΩ 3.4PF	2MΩ 3.4PF	27MΩ 2.5PF	50MΩ 2.5PF	50MΩ 2.5PF	50MΩ 2.5PF	9MΩ 3.4PF	4MΩ 7PF	4MΩ 7PF	8MΩ 7PF
<b>Over Range LED</b>	----	----	----	----	----	----	○	○	○	○	○
<b>Adapter</b>	○	○	○	○	○	○	○	○	○	○	○
<b>CARRY BOX</b>	----	○	○	----	○	○	○	○	----	----	----
<b>ACCESSORIES</b>	BP-250 BP-256N BP-356N	BP-250 BP-256N BP-276N BP-286 BP-356N	BP-250 BP-256N BP-276N BP-286 BP-356N	BP-250 BP-266 BP-366	BP-250 BP-266 BP-276N BP-286 BP-366	BP-250 BP-266 BP-276N BP-286 BP-366	BP-250 BP-266 BP-276N BP-286 BP-366	BP-250 BP-256N BP-276N BP-286 BP-356N	?	?	?
<b>PRICE (USD) (FOB TAIWAN)</b>	USD190	USD225	USD210	USD300	USD370	USD430	USD500 (2009/July)	USD430 (2009/Aug)	USD860	USD1270	USD2540

※ Specifications and appearance design subject to change without notice.